

**RF-7800M-AD250**  
**AN/PRC-117G DUAL**  
**CHANNEL ADAPTER**  
**PLATE FOR AN/VRC-103**  
**(AM-7588) 50-WATT**  
**MULTIBAND VEHICULAR**  
**AMPLIFIER ADAPTER**  
**(VAA)**

*A multi-channel upgrade*  
*for existing 50-watt*  
*vehicular installations*

The RF-7800M-AD250 Dual Channel Adapter Plate interfaces up to two JTEL-certified Software Communications Architecture (SCA) AN/PRC-117G(V)1(C) radios to an AM-7588 power amplifier (PA). The adapter allows existing installations of the AN/VRC-103 to update to dual channel JTRS-level multiband and wideband vehicular capabilities, while maintaining the legacy capabilities of traditional multiband vehicular radio systems.

The adapter also allows AN/PRC-117G transceivers to support the same field-proven capabilities as the AN/VRC-103, including SINCGARS and Havequick III ECCM, with full-circuit protection, DC filtering, VHF/Low FM (30-90 MHz) and UHF (225-400 MHz) collocation filters, and SATCOM Low Noise Amplifier (LNA) along with wideband communications from 225 to 2000 MHz.

With two channels, the adapter offers communications flexibility for a variety of missions. The first channel provides DC input power and up to 50 watts output power in the 30 to 512 MHz narrowband range, and up to 20 watts output power in the 225 to 2000 MHz wideband range. The second channel provides DC input power with up to 10 watts in the 30 to 512 MHz range, 20 watts in the SATCOM band, and 20 watts in the 225 to 2000 MHz wideband range.

The adapter includes a locking mechanism, RF cables and shock mount upgrade. AM-7588 accessories can be used with the adapter, including, Tactical Speakers, and X-Wing SATCOM-on-the-Move (SOTM), VHF/UHF Multiband Vehicular Whip and VHF/UHF GPS Multiband Vehicular Whip Antennas.



## Specifications for the RF-7800M-AD250

Power output		
	Channel 1	Channel 2
VHF	50 watts	10 watts
UHF	50 watts	10 watts
SATCOM	50 watts	20 watts
Wideband	20 watts	20 watts



The adapter plate supports single and dual channel operation, allowing existing AM-7588 installations to upgrade to the JTEL- certified Software Communications Architecture (SCA) of the AN/PRC-117G(V)1(C). This upgrade provides JTRS-level multiband and wideband vehicular capabilities while maintaining the legacy capabilities of traditional vehicular radio systems.



The dual channel configuration combines the advanced features of the AN/PRC-117G(V)1(C) with the proven performance of the AM-7588 to provide legacy multiband capabilities, secure line-of-sight (LOS) wideband networking, and global beyond-line-of-sight (BLOS) connectivity.

Accessories	
<b>RF-3184-AT320</b>	225-450 MHz Wideband Vehicular Antenna
<b>RF-3186-AT320</b>	512-2000 MHz Wideband Vehicular Antenna
<b>10513-0810</b>	Coaxial Cable, Type N to Type N
<b>RF-3183-AT013 or RF-390-AT001</b>	30-512 MHz Broadband Vehicular Antenna with Diplexer
<b>RF-3183-AT015 or RF-390-AT005</b>	30-512 MHz Broadband Vehicular Antenna
<b>10369-7212 (RG-213)</b>	Coaxial Cable BNC to BNC
<b>12011-0120 (RG400)</b>	Coaxial Cable TNC to BNC
<b>12006-9001-01</b>	SATCOM X-Wing Vehicular Antenna
<b>10369-7211 (RG-213) or 10513-0811 (LMR 400DB)</b>	Coaxial Cable, BNC to Type N
<b>RF-3071-AT230</b>	L1/L2 Active GPS, Vehicular Antenna with Cable
<b>RF-5980-SA001</b>	Tactical Amplifier/Speaker
<b>10535-0706-A009</b>	Speaker to 4-pin MIL power connector
<b>10535-0707-A009</b>	Speaker Audio Cable



**RF Communications** | 1680 University Ave. | Rochester, NY USA 14610 | 585.244.5830 | [www.harris.com](http://www.harris.com)

Get quotes real-time at eHarris. Order parts online at: <https://premier.harris.com/rfcommsales>

This Information was approved for all publishing per the ITAR as "basic marketing in information of defense articles" or as "advertising printed matter" per the EAR. Specifications are subject to change without notice. ©2011 Harris Corporation 4/11 DS-444B